

Power Supplies

Single-phase input voltage
10 A, 20 A




10 A
240 W
24 V DC (SELV)
115/230 V AC (Auto-Select)

BAE0002

BAE PS-XA-1W-24-100-004

90...132 V AC; 180...264 V AC/210...375 V DC
115 V AC < 30 A/230 V AC < 60 A
47...63 Hz
T6.3 A/250 V AC internal
22.5...28.5 V DC
±0.03 %/°C
100 mV
115 V AC > 25 ms/230 V AC > 30 ms
Green LED
Red LED
89 %
Forward characteristic
> 40 kHz (typically)
3000 V AC
100 MΩ
< 1 s
-25...+71 °C
-2.5 %/°C of +61 °C
Yes
IP 20
DC OK output relay
Air convection
Metal
1.0 kg
CE, UL/cUL, TÜV




L, N	Input terminals
PE	PE connection
Vo -	Output terminal -
Vo +	Output terminal +
Rdy	Ready output

20 A
480 W
24 V DC (SELV)
115/230 V AC (Auto-Select)



BAE0003

BAE PS-XA-1W-24-200-005

90...264 V AC/120...370 V DC
115 V AC < 25 A/230 V AC < 50 A
47...63 Hz
T10 A/250 V AC internal
22.5...28.5 V DC
±0.03 %/°C
100 mV
115 V AC > 25 ms/230 V AC > 30 ms
Green LED
Red LED
89 %
Forward characteristic
> 65 kHz (typically)
3000 V AC
100 MΩ
< 1 s
-25...+71 °C
-2.5 %/°C of +56 °C
Yes
IP 20
DC OK output relay
Air convection
Metal
1.92 kg
CE, UL/cUL, TÜV



L, N	Input terminals
PE	PE connection
Vo -	Output terminal -
Vo +	Output terminal +
Rdy	Ready output



Single-phase
power supplies
Three-phase
power supplies

